



# FLEXISCAN

## 110° PIR SECURITY SENSOR



- 240V
- Detection Scan: 110°
- Detection Range: 18m
- Time on: 5s to 10m
- Lux Setting
- Max Load: 2400W
- IP66

LED Compatible  
 Passive Infra-red technology  
 Multi-segmented optical lens for better detection  
 3-Wire design for greater reliability  
 IP66 Weather-resistant Rated  
 Wall or ceiling installation  
 Heavy duty switching circuitry, suitable for large loads  
 Easy to mount  
 Max Load: 2400W Incandescent  
 1200W Inductive  
 Power consumption: 0.7W  
 Operating Temp: -5 to 45 degrees Celsius  
 5-Year Warranty

Code:	<b>18562/..</b>
<b>09</b> BEIGE	9 326411 856281 >



# UNI-SCAN

## 180° PIR SECURITY SENSOR



- 240V
- Detection Scan: 180°
- Detection Range: 12m
- Time on: 10s to 4m
- Lux Setting
- Max Load: 1000W
- IP44

Passive Infra-red technology  
 Multi-segmented lens for better detection  
 3-Wire design for greater reliability  
 IP44 Weather-resistant Rated  
 Max Load: 300W Incandescent  
 100W Inductive  
 Operating Temp: -5 to 45 degrees Celsius  
 2-Year Warranty

Code:	<b>18060/..</b>
<b>05</b> WHITE	9 312641 180616 >
<b>06</b> BLACK	9 312641 180609 >